



AMPLIFIER — VOLUME CONTROL — SPEAKER POWER DISTRIBUTION UNIT REPLACEMENT PARTS LIST

(L & R Denotes Left and Right Channel)

Item	Description	Part No.	Item	Description	Part No.
	LAMPS				
B1	Lite Bulb	ST-9626	CR3 -	1N4174B 1W Zener Diode	44788
BR1 L&R	Dual Lamp	43518	CR4 -	1N625 Diode	43555
	CAPACITORS		CR5 -	600 PRV Plastic Rectifier	44875
C1 L&R	.001 mfd 200V.	41503	CR6 -	Bridge Rectifier	43509
C2 L&R	.39 mfd 100V.	43574	CR7 -	600 PRV Plastic Rectifier	44875
C3 L&R	125 mfd 10V.	43539	CR8 -	600 PRV Plastic Rectifier	44875
C4 L&R	.015 mfd 200V.	41505	F1 -	Slo-Blo Fuse 1 Amp 250V.	ST-4332
C5 L&R	.039 mfd 200V.	43572		SOCKETS	
C6 L&R	150 mmfd ceramic disc	33438	J1 -	9 Contact Tube Socket	14799
C7 L&R	125 mfd 10V.	43539	J2 -	3 Pin Socket	44927
C8 L&R	.39 mfd 100V.	43574	J3 -	6 Prong Min. Socket	18634
C9 L&R	2200 mmfd ceramic disc	30578	J4 -	7 Circuit Combo Plug Housing (Wht)	44810
C10 L&R	50 mmfd ceramic disc	44774	J5 -	Dual Photocell Socket (Part of 44798)	44799
C11 L&R	.47 mfd 100V.	43535	J6 -	10 Cir. M-N-L Motor Mount Pin Housing	V-7038
C12 -	100 mfd 64V.	41501	J7 -	Relay Socket	44806
C13 -	250 mfd 64V.	43536	J8 -	6 Cir. M-N-L Motor Mount Pin Housing	V-7030
C14 L&R	50 mfd 40V.	42954	J9 -	6 Cir. M-N-L Soc. Housing	V-7005
C15 L&R	125 mfd 10V.	43539	J10 -	3 Cir. M-N-L Soc. Housing	V-7047
C16 L&R	.22 mfd 200V.	43558	J11 -	12 Cir. M-N-L Soc. Housing	V-7021
C17 -	150 mfd 25V.	43490	J12 -	3 Cir. M-N-L Soc. Housing	V-7047
C18 L&R	.47 mfd 100V.	43535		MISCELLANEOUS	
C19 -	Not used		K1 -	Relay 24V.D.C. (Also In Rcvr)	43561
C20 -	250 mfd 64 V.	43536	M1 -	Volume Control Motor Assem.	44864-A
C21 L&R	.18 mfd 100V.	44776	MPU1 -	Magnetic Cartridge (M44MR)	43467
C22 L&R	.1 mfd 200V.	44775	PC1 -	Dual Photocell Lamp Module	44798
C23 L&R	.068 mfd 200V.	41507	P1 -	Top Mount Plug - 9 Pin	38706
C24 L&R	.0033 mfd 200V.	43524	P2 -	Dual Input Cable Assembly Lamp Module Same as 43439	44926-A
C25 L&R	.0068 mfd 200V.	43525	P3 -	6 Pin Molded Plug & Cable	44773
C26 L&R	.015 mfd 200V.	41505	P4 -	7 Cir. Combo Cap Housing	44811
C27 L&R	.047 mfd 200V.	41506	P5 -	Not used	
C28 -	.022 mfd 200V.	41334	P6 -	10 Cir. M-N-L Motor Mount Socket Housing	V-7039
C29 -	.022 mfd 200V.	41334	P7 -	Not used	
C30 -	9 mfd 60V. non-polarized	44762	P8 -	6 Cir. M-N-L Motor Mount Socket Housing	V-7031
C31 L&R	.47 mfd 100V.	43535	P9 -	6 Cir. M-N-L Pin Housing	V-7004
C32	250 mfd 25V.	43537	P10 -	3 Cir. M-N-L Pin Housing	V-7046
C33 -	250 mfd 64V.	43536	P11 -	12 Cir. M-N-L Pin Housing	V-7020
C34 L&R	.01 mfd 200V.	43534	P12 -	3 Cir. M-N-L Pin Housing	V-7046
C35 L&R	200 mfd 10V.	43538	PEC1 -	Volume Control PEC	44715
C36 L&R	125 mfd 10V.	43539		TRANSISTORS	
C37 -	50 mfd 40V.	42954	Q1 L&R	2N3391A	43565
C38 -	1500 mfd 60V.	43508	Q2 L&R	2N3391A	43565
C39 -	1500 mfd 60V.	43508	Q3 L&R	2N3417	43548
C40 L&R	1500 mfd 60V.	43508	Q4 L&R	2N3405	43530
C41 L&R	15 mfd 35V. RMS non-polarized	40288			
	CIRCUIT BREAKER				
	DIODES AND RECTIFIERS				
CB1 -	1 Amp Circuit Breaker	44782			
CR1 L&R	1N625 Diode	43555			
CR2 L&R	1N295 Diode	43556			