



Model 461

PARTS LISTED ALSO INCLUDES PARTS IN STEREO KIT #2174

STEREO AMPLIFIER No. 48350-1A PARTS LIST
(L and R denotes Left and Right Channel)

Item	Description	Part No.	Item	Description	Part No.
CAPACITORS			C51	.0022 mf Ceramic Disc	50104
C1 L&R	.027 mf 250V	48949	C52	.0022 mf Ceramic Disc	50104
C2 L&R	150 pf Ceramic Disc	45789	C53	10 mf 63V	50105
C3 L&R	2.2 mf 25V	49146	RESISTORS		
C4 L&R	.015 mf 250V	48947	Note: All resistors are 1/2 watt 5% tolerance unless otherwise noted.		
C5 L&R	.1 mf 250V	47421	R1 L&R	1K Min. P.C. Control	49272
C6 L&R	.1 mf 250V	47421	R2 L&R	470 ohm 1/4W	49264
C7 L&R	10 mf 25V	48938	R3 L&R	510 1/4W	49265
C8 L&R	150 pf Ceramic Disc	45789	R4	27K 1/4W	49269
C9 L&R	.47 mf 100V	48951	R5	2.2K 1/4W	48042
C10	.22 mf 100V	48941	R6	560K 1/4W	49266
C11	220 mf 10V	49271	R7	33K 1/4W	49268
C12 L	.1 mf 250V	47421	R8 L	56K 1/4W	49267
C13 R	.1 mf 250V	47421	R9 R	56K 1/4W	49267
C14 L	.015 mf 63V	48947	R10	24K 1/4W	42270
C15 R	.015 mf 63V	48947	R11 L	47K	13015
C16 L	.015 mf 63V	48947	R12 R	47K	13015
C17 L	.015 mf 63V	48947	R13	1K Min. P.C. Control	43522
C18 R	.015 mf 63V	48947	R14 L&R	150K Min. P.C. Control	49284
C19 R	.015 mf 63V	48947	R15 L&R	12K	32206
C20 L	150 pf	45789	R16 L&R	2.7K	13182
C21 R	150 pf	45789	R17 L&R	2700 ohm 10%	13182
C22 L	2200 pf 63V	49286	R18 L&R	180 ohm 1W	49692
C23 L	6800 pf 63V	49287	R19 L&R	100 ohm 1W	35329
C24 R	6800 pf 63V	49287	R20 L&R	150 ohm Min. P.C. Control	50107
C25 R	2200 pf 63V	49286	R21	Not Used	
C26 L&R	.047 mf 250V	47422	R22 L&R	2700 ohm 10%	13182
C27 L&R	10 mf 75V	49279	R23 L&R	2700 ohm 10%	13182
C28 L&R	22 mf 75V	49278	R24 L&R	100 ohm 5W 10%	36846
C29 L&R	100 mf 70V	49285	R25 L&R	.33 ohm 10W 10%	49297
C30 L&R	150 pf Ceramic Disc	45789	R26 L&R	100 ohm 5W 10%	36846
C31	220 mf 63V	48942	R27 L&R	.33 ohm 10W 10%	49297
C32	47 mf 6.3V	49414	R28	220 ohm 1W 10%	35326
C33	.047 mf 250V	47422	R29	22 ohm	14234
C34	160 mf 64V	44892	R30	1K 10%	16224
C35	25 mf 25V	49601	R31	25K Min. P.C. Control	49416
C36	25 mf 25V	49601	R32	27K 10%	15403
C37	160 mf 64V	44892	R33	1K 10%	16224
C38 R	100 mf 70V	49285	R34	2700 ohm 2W	50106
C39 L	1500 mf 60V	49142	R35	6200 ohm 1W	49412
C40 L	100 mf 70V	49285	R36	330 ohm	38673
C41 R	1500 mf 60V	49142	R37	820 ohm	46943
C42	.033 mf 400V	49417	R38	20K 10%	49411
C43	.033 mf 400V	49417	R39	1200 ohm	46249
C44	2000 mf 75V	48928	R40	1200 ohm	46249
C45	20 mf 16V	48038	R41	15 ohm 1W	39671
C46 L&R	470 pf	33762	R42 R	22 ohm 2W 10%	49298
C47 L&R	2200 pf	30578	R43 R	10K 10%	13388
C48 L&R	150 pf Ceramic Disc	45789			
C49 L	.0022 mf Ceramic Disc	50104			
C50 R	.0022 mf Ceramic Disc	50104			

Call for printed circuit board diagrams.