



Complete Listing of Replacement Transformers

for

ALL 1937 and 1938 BROADCAST RECEIVERS

Listed in Rider's Manual Vol. VIII

No. 243-S

Supplement

THORDARSON ELECTRIC MFG. CO.

500 W. HURON ST., CHICAGO, ILL.

Demand "Power by Thordarson"

THORDARSON TRANSFORMER REPLACEMENT ENCYCLOPEDIA

MODEL	Power Trans.	First Filter Choke	Second Filter Choke	First Audio Trans.	Second Audio Trans.	Output Trans.	MODEL	Power Trans.	First Filter Choke	Second Filter Choke	First Audio Trans.	Second Audio Trans.	Output Trans.
AIRKING PRODUCTS CORP.							BELMONT RADIO CORP.						
11F.....	T-13R14	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	415, series A & B	Special	☆	☆	☆	☆	T-13S38
72, 73, 250, 260.	☆	T-13C27	☆	☆	☆	T-13S38	588 Series A, 787 Series A, 878 Series A & B, 879 Series A, 890 Series A.....	T-13R12	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
261.....	T-13R11	☆	☆	☆	☆	T-13S38	589.....	T-13R11	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
700, 705, 710, 715, 2001, 730, 731, 214, 1001...	☆	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	602.....	☆	☆	☆	☆	☆	T-13S38
ALLIED RADIO CORP.							740, 840.....	T-13R13	☆	☆	☆	☆	☆
A-9701, A-9702, A-9703, A-9704, A-9715, A-9716, A-9717, A-9718..	☆	T-13C27	☆	☆	☆	T-13S38	804.....	Special	Special	☆	☆	T-78D46	T-81S01
A-9705, A-9735, A-9710, A-9710E, A-9711, A-9711E, A-9712, A-9712E.	☆	T-13C28	☆	☆	☆	T-13S38 T-17S57 T-57S01	822.....	☆	☆	☆	☆	T-78D46	T-81S01
A-9720, A-9721, A-9722, Z3, A-9807, A-10505, 5X, A-10506, 6W, A-10507, 7M	T-13R12	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	848, 849.....	☆	Special	☆	☆	☆	T-13S38 T-17S57 T-57S01
A-9724, A-9725, A-9726, A-9813..	☆	☆	☆	☆	T-13A35 T-33A91 T-57A41	T-13S38 T-17S57 T-57S01	1170, 1172, 1170B.....	T-13R15	☆	☆	☆	T-17D01	T-13S41
A-9728, A-9729, A-9730, A-10508, 6P.....	☆	T-13C26	☆	☆	T-78D46	T-81S01	1174.....	T-13R15	T-13C27	☆	☆	T-17D01	T-13S41
A-9733, A-9734..	Special	☆	☆	☆	T-13A35 T-33A91 T-57A41	T-13S38 T-17S57 T-57S01	DAVID BOGEN CO., INC.						
A9775, A9860, chassis B1.....	T-13R11	☆	☆	☆	☆	T-13S38	2.5, 5 and 10 meter Super....	T-13R12	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
9776, A-9777, A-9778, Z5.....	Special	T-13C28	☆	☆	T-78D46	Special	BREITING RADIO MFG. CO.						
A-9802, A-9805, A-10502, A-10503, 6Y.....	☆	T-13C28	☆	☆	☆	T-13S38 T-17S57 T-57S01	Breiting 14.....	T-13R15	☆	☆	☆	☆	T-75S75
ANDREA							BROWNING DRAKE CORPORATION						
1A5, 5A5, A5L, 2A5, 6A5, A5S, 1A7, 5A7, A7L..	T-13R12	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	Larcoflex.....	T-13R06	T-13C30	☆	T-13A34 T-29A99 T-47A25	T-13A35 T-33A91 T-57A41	T-13S38 T-17S57 T-57S01
2D7, 4D7, 6D7, 8D7, D7S, 1D7, 3D7, 5D7, 7D7, D7L, 1B6, 3B6, B6L, 2B6, 4B6, B6S.....	T-13R13	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	CAPEHART CORP.						
1D10, 2D10, 3D10, 4D10, 5D10, 6D10, 7D10, 8D10, 9D10, 10D10 Chassis, D10L, Chassis, D10S...	T-13R14	T-75C49 T-53C19	☆	☆	☆	T-13S38 T-17S57 T-57S01	200F Tuner	T-13R14	T-75C49 T-53C19	☆	☆	T-13A35 T-33A91 T-57A41	Special
MI, CA5, 410, UC4, 411, UC4L, 520 UD5S, 521, UD5L.....	☆	T-13C28	☆	☆	☆	T-13S38 T-17S57 T-57S01	400F Tuner.....	T-13R13	T-57C53	☆	☆	☆	☆
1401, 1403, 1405, 1407, 1409, UD14L...	☆	T-57C53 and T-13C27	☆	☆	☆	T-13S38 T-17S57 T-57S01	400F Treble Amp.....	T-13R15	T-13C30 T-17C00B	☆	☆	☆	Special
616, 617, 618, D6B.....	Special	T-13C28	☆	☆	☆	T-13S38 T-17S57 T-57S01	CHAMPION RADIO						
ANSLEY RADIO LABORATORIES							50 UD.....	☆	T-13C27	☆	☆	☆	T-13S38
D9, D10, D17, D18, U10, U11, 677-78, D-24, D-25, 7152.....	☆	T-13C27	☆	☆	☆	T-13S38 T-17S57 T-57S01	521 UD, 543 ID	☆	☆	☆	☆	☆	T-13S38
AUTOMATIC RADIO MFG. CO.							525 DWG, 526 DW.....	T-13R12	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
M10, M20.....	Special	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	CLIMAX RADIO & TELEVISION						
B30, Series I....	☆	T-13C27	☆	☆	☆	T-13S38 T-17S57 T-57S01	Diamond-4 tube 2 Band, Duke, B, C, D, E, RBT, T, Q-69, Z55.....	☆	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
B30, Series II, B40, Series II...	☆	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	AD, 5 tube skip band, AC-60, AC-61, AC-64, AC-64B, AC-65	T-13R12	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
B70, B80.....	☆	T-13C29	☆	☆	☆	T-13S38 T-17S57 T-57S01	AH, AHE, HE, JE, SBT, JEFT	☆	T-13C28	☆	☆	☆	T-13S38 T-17S57 T-57S01
850.....	☆	☆	☆	☆	☆	T-13S38	AJ.....	☆	☆	☆	☆	T-78D46	T-81S01
☆ None Required.							AKE.....	Special	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
							F, G, R, U60, U61, U64, U64B, U65.....	☆	T-13C27	☆	☆	☆	T-13S38
							JL.....	Special	☆	☆	☆	☆	T-13S38
							MJME, MEFT.	T-13R13	☆	☆	☆	☆	T-13S38
							CONTINENTAL RADIO & TELEVISION						
							5Z, 150-5Z, 155-5Z, 985-5Z, 990-5Z, 5M, 5X, 160-5X, 980-5X	T-13R11	☆	☆	☆	☆	T-13S38
							6P, 7J.....	Special	T-13C26	☆	☆	T-78D46	T-81S01
							6W, 165-6W, 975-6W, 7M, 7MU.....	T-13R12	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
							8K.....	T-13R13	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01

THORDARSON TRANSFORMER REPLACEMENT ENCYCLOPEDIA

MODEL	Power Trans.	First Filter Choke	Second Filter Choke	First Audio Trans.	Second Audio Trans.	Output Trans.	MODEL	Power Trans.	First Filter Choke	Second Filter Choke	First Audio Trans.	Second Audio Trans.	Output Trans.
CONTINENTAL RADIO & TELEVISION—(Cont.)							EMERSON RADIO & PHONOGRAPH CO.						
11S.....	Special	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	AD108, AD110, AD125, Chassis AA: AA131, late, AE, AE163, AL, AL-130, AL LW 130, AL132, AL LW 132, AL149, AL LW 149, AL168, AL LW 168, Chassis AL LW, AL, AL164, AH, AH162, Chassis AM: AM131, AM169, AM187, Chassis AP: AP171, AP173, AP174, AP176, AP180, AP185.....	☆	☆	☆	☆	☆	T-13S42
150-6Y, 155-6Y, 985-6Y, 990-6Y..	☆	T-13C28	☆	☆	☆	T-13S38 T-17S57 T-57S01	Chassis AA, AA131 (Early Model)...	☆	T-13C27	☆	☆	☆	T-13S38
CORONA RADIO & TELEVISION							Chassis AG, AG-151.....	☆	☆	☆	☆	☆	T-13S42
212, 214.....	Special	T-13C28	☆	☆	☆	T-13S38 T-17S57 T-57S01	Chassis AJ, AJ130, AJ137, AJ149, AF, AF171, AF173, AF176, AF179, AF180, AF185.....	☆	☆	☆	☆	☆	T-13S43
CROSLEY RADIO CORP.							Chassis AR: AR171, AR173, AR174, AR176, AR180, AR185, AT, 170, AT172, AT181, Chassis S: S147, S151, Chassis Z: Z117, Z122, Z133, Z141, Z150, Z159, Z160, Z135	T-13R12	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
506, 566, 676.... 416	☆	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	Chassis AS: AS170.....	Special	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
517, 547, Fiver, Teletune Fiver..	T-13R11	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	Chassis DLW: D134 LW, D136 LW, D138 LW, D139 LW, D140 LW, D142 LW, D146 LW.....	T-13R14	T-13C30	☆	☆	☆	T-13S38 T-17S57 T-57S01
537.....	Special	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	Chassis G, G127	☆	T-13C27	☆	☆	☆	T-13S38 T-17S57 T-57S01
596.....	☆	T-13C28	☆	☆	☆	T-13S38 T-17S57 T-57S01	Chassis L: L143, Chassis R: R152, R153, R156, R158	T-13R11	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
656, 6656, 666, 6666.....	T-13R12	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	Chassis M: M134, M136, M138, M139, M140, M142, M146....	☆	T-13C30	☆	☆	☆	T-13A35 T-33A91 T-57A41
716, 726, 736....	T-13R13	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	P117, P135.....	Special	T-13C26	☆	☆	☆	Special
926, 1126.....	T-13R14	☆	☆	☆	T-13A35 T-33A91 T-57A41	T-13S38 T-17S57 T-57S01	Chassis X, X143.....	T-13R15	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
1216, 1336.....	T-13R15	☆	☆	☆	T-13A35 T-33A91 T-57A41	T-13S41	ESPEY MFG. COMPANY						
1516.....	Special	☆	☆	☆	T-13A35 T-33A91 T-57A41	T-13S41	675.....	☆	T-13C28	☆	☆	☆	T-13A35 T-33A91 T-57A41
DETROLA RADIO CORP.							5111.....	☆	T-13C28	☆	☆	☆	Special
130, 134-X, 157-A.....	☆	T-13C26	☆	☆	☆	T-13S38 T-17S57 T-57S01	7111.....	T-13R15	☆	☆	☆	☆	T-13S41
134A, 134AB, 134AZ, 135, 135E, 137, 158A, 162, 172..	☆	T-13C27	☆	☆	☆	T-13S38 T-17S57 T-57S01	7151, 7153.....	☆	T-13C30	☆	☆	☆	Special
136, 139, 139E, 149, 149E, 154E.	Special	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	FADA RADIO & ELECTRIC CO.						
140, 148, 150, 159, 162A, 168..	☆	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	211 (220 v.), 211 B (220 v.), 311 (220 v.), 1262	☆	T-13C28	☆	☆	☆	T-13S38 T-17S57 T-57S01
144B, 144C, 145B, 145CR...	Special	☆	☆	☆	☆	T-13S38	212.....	T-13R14	T-13C30 T-75C49	☆	☆	☆	T-13S41
146.....	T-13R12	☆	☆	☆	☆	T-13S38	216, 316.....	☆	T-13C30	T-13C30	☆	☆	Special
147A-B-CR, 147, 147E, 155X, 165	T-13R13	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	242.....	☆	☆	☆	☆	☆	T-13S43
163.....	T-13R15	☆	☆	☆	☆	Special	246.....	Special	T-13C26	☆	☆	☆	T-13S43
167, 169.....	☆	T-13C28	☆	☆	☆	T-13S38 T-17S57 T-57S01	254, 350, 351, 354	Special	☆	☆	☆	☆	T-13S41
DEWALD RADIO							255, 265, 1255, 1265.....	T-13R12	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
400, 405, 522....	☆	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	261.....	☆	T-13C27	☆	☆	☆	T-13S38 T-17S57 T-57S01
528, 528LW, 629, 629LW, 700A, 700A LW, 703, 703 LW, 1200...	☆	☆	☆	☆	☆	T-13S42	312.....	Special	T-13C27	☆	☆	☆	T-13S41
529, 529LW....	T-13R11	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	DICTOGRAPH PRODUCTS CO.						
633, 633LW, 633S	☆	☆	☆	☆	☆	T-13S42	91134, 91134A, 91168, 91175....	☆	T-13C27	☆	☆	☆	
635, 635 LW....	T-13R12	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01							
700, 700 LW....	☆	T-13C28	☆	☆	☆	T-13S38 T-17S57 T-57S01							

☆ None Required.

THORDARSON TRANSFORMER REPLACEMENT ENCYCLOPEDIA

MODEL	Power Trans.	First Filter Choke	Second Filter Choke	First Audio Trans.	Second Audio Trans.	Output Trans.	MODEL	Power Trans.	First Filter Choke	Second Filter Choke	First Audio Trans.	Second Audio Trans.	Output Trans.
FAIRBANKS, MORSE & COMPANY							GAROD RADIO CORP. (Cont.)						
5C, 6A.....	T-13R12	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	830A, 831A.....	☆	T-13C29	☆	☆	☆	T-13S42
5D.....	☆	☆	☆	☆	T-78D46	T-81S01	930, 930D, 930KC, 931, 931D, 931KC...	☆	T-13C27	☆	☆	T-13A35	T-13S38 T-17S57 T-57S01
6C, 73, 73C3B, 73T3B...	Special	T-13C27	☆	☆	T-78D46	T-81S01	930A, 931A.....	☆	T-13C29	☆	☆	☆	T-13S41
8A, 9A.....	T-13R13	☆	☆	☆	☆	T-13S42	1240, 1240E, 1240LC, 1650, 1650H, 1650 LC.	☆	T-13C29	☆	☆	T-13A35 T-33A91 T-57A41	Special
12A.....	T-13R15	☆	☆	☆	☆	T-13S41	5240.....	Special	T-54C50 T-75C51	☆	☆	Special	Special
12C6, Chassis 120.....	Special	☆	☆	☆	T-13A35 T-33A91 T-57A41	T-13S41	GENERAL ELECTRIC CO.						
42, 42 CIB, 42 TOB.....	☆	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	E50, E52, F53...	Special	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
43, 43CIB, 43TIB.....	Special	T-13C26	☆	☆	☆	T-13S43	U-50.....	☆	☆	☆	☆	☆	T-13S43
57, 57TO, 58, 58T1, 58T2.....	T-13R11	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	E-51.....	☆	T-13C27	☆	☆	☆	T-13S38 T-17S57 T-57S01
68, 68T6, 69, 69T7.....	☆	T-13C28	☆	☆	☆	T-13S38 T-17S57 T-57S01	U51, U55.....	Special	☆	☆	☆	☆	T-13S43
72, 72C2, 72C3, 72T3.....	Special	☆	☆	☆	☆	T-13S42	F63, F65, F66, F70, F75, E79, F81, F86.....	T-13R12	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
91, 91C4, 91C5, 91TH.....	T-13R13	☆	☆	☆	☆	T-13S42	FB72, FB73, U70, U75, FB76, FB77	Special	☆	☆	☆	T-78D46	T-81S01
FEDERATED PURCHASER							E-115.....	Special	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
1940.....	T-13R15	☆	☆	☆	☆	Special	E126, E129.....	Special	☆	☆	☆	T-13A35 T-33A91 T-57A41	T-13S38 T-17S57 T-57S01
FIRESTONE							E-155.....	Special	☆	☆	☆	T-17D01	T-13S41
7405-1, Airchief.	☆	T-13C27	☆	☆	☆	T-13S38 T-17S57 T-57S01	GENERAL HOUSEHOLD UTILITIES CO.						
7406-1, 7407-1...	Special	T-13C26	☆	☆	T-78D46	T-81S01	Chassis 4NB, 410, 411.....	Special	Special	☆	☆	☆	T-13S38 T-17S57 T-57S01
7422-3.....	☆	T-13C28	☆	☆	☆	T-13S42	5J, 5L, 5R, 5H, 5Q, 532, 542, 551, 553, 555, 564, 566, 572, 573....	T-13R11	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
FREED MFG. CO.							5NB, 510.....	☆	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
FE33, FE50, FE51L, P351L...	☆	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	5M, 590.....	☆	Special	☆	☆	☆	T-13S38 T-17S57 T-57S01
FE60, FE62....	☆	T-13C27	☆	☆	☆	T-13S38 T-17S57 T-57S01	6M, 6N, 7M, 7Q, 8H, 631, 643, 654, 723, 731, 733, 735, 755, 823, 831, 833, 835....	T-13R12	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
FE69-X.....	T-13R12	☆	☆	☆	☆	T-13S38	7NB, 711.....	Special	T-13C26	☆	☆	T-78D46	T-81S01
GALVIN MFG. CO.							9E, 11G, 941, 1191, 1191B....	T-13R13	☆	☆	☆	T-13A35 T-33A91 T-57A41	T-13S38 T-17S57 T-57S01
5-1, 5T.....	T-13R11	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	12B, *12W, 1291, *1297.....	T-13R15	☆	☆	☆	☆	T-13S38 *T-13S41
5-2, 5T-1, 5T-2, 5Y, 6A, 6-1.....	T-13R12	☆	☆	☆	☆	T-13S38	GENERAL TELEVISION AND RADIO CORP.						
6-2, 6T, 6Y.....	T-13R12	☆	☆	☆	☆	T-13S42	510.....	T-13R12	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
10-1, 10Y.....	T-13R13	☆	☆	☆	☆	T-13S42	533.....	☆	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
GAMBLE SCOGMO INC.							543.....	☆	T-13C27	☆	☆	☆	T-13S38
11B, 42DL670...	Special	T-13C30	☆	☆	☆	T-13S41	745.....	T-13R04	T-13C30	☆	☆	☆	T-13S38 T-17S57 T-57S01
70, 2516.....	T-13R05	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	GILFILLAN BROS.						
47LL, 47R, 47RL, 740, 762, 774....	T-13R13	☆	☆	☆	☆	T-13S38	521T-C, 711T, 731T-C.....	T-13R12	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
460.....	T-13R11	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	1331C.....	T-13R14	☆	☆	☆	T-13A36	T-13S38 T-17S57 T-57S01
510, 511, 787, 810	T-13R12	☆	☆	☆	☆	T-13S38	GOODYEAR SERVICE						
550 AC.....	T-13R03	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	588.....	T-13R11	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
822, 850 B.....	☆	☆	☆	☆	T-78D46	T-81S01	602.....	☆	T-13C29	☆	☆	☆	T-13S42
1170.....	T-13R14	☆	☆	☆	T-17D01	T-13S38 T-17S57 T-57S01	741.....	T-13R13	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
5953A.....	☆	☆	☆	☆	T-13A35 T-33A91 T-57A41	☆	1173.....	T-13R14	☆	☆	☆	T-17D01	T-13S38 T-17S57 T-57S01
GAROD RADIO CORP.													
380, 380D, 381, 381D, 381 KC, 880 KC.....	T-13R13	☆	☆	☆	☆	T-13S42							
620, 731, 830, 830C, 830D, 830KC, 831, 831C, 831D, 831 KC.....	☆	T-13C27	☆	☆	☆	T-13S38 T-17S57 T-57S01							

☆ None Required.

THORDARSON TRANSFORMER REPLACEMENT ENCYCLOPEDIA

MODEL	Power Trans.	First Filter Choke	Second Filter Choke	First Audio Trans.	Second Audio Trans.	Output Trans.	MODEL	Power Trans.	First Filter Choke	Second Filter Choke	First Audio Trans.	Second Audio Trans.	Output Trans.
THE HALLICRAFTERS, INC.							MAJESTIC RADIO & TELEVISION CO.-(Cont.)						
5T, S14, Sky Chief, Sky Buddy	T-13R12	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	620.....	T-13R12	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
H8PA.....	T-13R11	T-13C27	☆	☆	☆	Special	800.....	☆	T-13C28	☆	☆	☆	T-13S42
S11, Super Sky Rider, S-12, Comm. Sky Rider	T-13R14	T-13C30	☆	☆	T-13A35 T-33A91 T-57A41	Special	1250.....	T-13R15	☆	☆	☆	☆	T-13S41
S15 Sky Challenger.....	T-13R13	T-13C28	☆	☆	☆	Special	MIDWEST RADIO CORP.						
SX-16 Super Sky Rider '38...	T-13R14	T-13C30	☆	☆	T-13A35 T-33A91 T-57A41	Special	SW5-36, 6-37, 7-36, 7-37, AC DC	☆	T-13C27	☆	☆	☆	T-13S38 T-17S57 T-57S01
HALSON RADIO MFG. CO.							6-33.....	T-13R03	☆	☆	☆	☆	Special
25.....	☆	T-13C27	☆	☆	☆	T-13S38 T-17S57 T-57S01	6-34.....	T-13R04	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
35, 104, 106.....	T-13R11	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	6 Tube Battery 8-31.....	☆	☆	☆	☆	T-78D46	T-81S01
102, 103, 161, 162, 310, 711....	☆	T-13C28	☆	☆	☆	T-13S42	6-38, 7-38, ACDC, 8-38....	☆	T-13C28	☆	☆	☆	T-13S42
HARRIS MFG. CO.							7-36 Batt., 7-37 Batt., 7-38 Batt., 8-38 Batt.....	Special	T-13C26	☆	☆	T-78D46	T-81S01
500, 501W, 600, 700, 701W, 900, 1201W.....	T-13R13	☆	☆	☆	T-13A35 T-33A91 T-57A41	T-13S38 T-17S57 T-57S01	7-37 AC.....	T-13R12	☆	☆	☆	☆	T-13S38
800, 1000.....	☆	T-13C28	☆	☆	T-13A35 T-33A91 T-57A41	T-13S38 T-17S57 T-57S01	8-33 early, 9-31 9-31-45G, 9-32, 11-31.....	T-13R06	T-13C30	☆	☆	T-13A35 T-33A91 T-57A41	T-13S38 T-17S57 T-57S01
HERBERT H. HORN							8-33 4 and 5 band	T-13R06	☆	☆	☆	☆	Special
16MT.....	T-13R13	T-13C30	☆	☆	T-13A35 T-33A91 T-57A41	T-13S38 T-17S57 T-57S01	9-38 ACDC, 10-38 ACDC, 11-37 ACDC....	☆	T-13C29	☆	☆	☆	T-13S42
HOWARD RADIO CO.							10-37 ACDC....	☆	T-13C29	☆	☆	T-13A35 T-33A91 T-57A41	Special
5B.....	☆	☆	☆	☆	☆	T-13S43	11-37.....	T-13R13	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
67C, 67T, 68, 256, S256, 268, 626, 1626.....	T-13R12	☆	☆	☆	☆	T-13S42	12-33.....	T-13R08	☆	☆	☆	T-17D01	T-13S38 T-17S57 T-57S01
56.....	☆	☆	☆	☆	☆	T-13S38	12-38.....	T-13R14	☆	☆	☆	☆	T-13S41
118, 218.....	T-13R12	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	12-38 Batt.....	Special	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
214.....	Special	☆	☆	☆	T-74C30	T-13S41	14-37.....	T-13R15	☆	☆	☆	Special	Special
259, S259.....	☆	T-13C27	☆	☆	☆	T-13S42	14-37 Int.....	T-13R09	T-54C50	☆	☆	Special	Special
INTERNATIONAL RADIO CORP.							14-37A.....	T-13R14	☆	☆	☆	☆	Special
10, 11, 12, 13, 14, 15, 16, "Classic," L, 56X, 86X....	☆	☆	☆	☆	☆	T-13S42	16-38 AC.....	Special	☆	☆	☆	☆	T-13S41
21, 22, 23, 76X, 150, 151, 676X, 1019.....	☆	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	18 Imperial.....	T-13R09	T-75C51 T-54C50	☆	☆	Special	Special
35, 36.....	T-13R11	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	Regal.....	Special	T-75C51 T-54C50	☆	☆	☆	Special
JACKSON BELL							MONTGOMERY WARD & COMPANY						
84.....	T-13R01	☆	☆	☆	☆	T-13S38	62-226, 62-228, 62-259, 62-267, 62-277, 62-308, 62-318, 62-408, 62-418.....	T-13R12	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
LAFAYETTE RADIO MFG. CO.							62-254.....	☆	☆	☆	☆	☆	T-13S43
1, 2, M31, M37, 2Y2280.....	T-13R03	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	62-310, 62-326, 62-336, 62-410, 62-426, 62-436....	☆	☆	☆	☆	T-78D46	T-81S01
EB9, A18, EB8..	☆	T-13C28	☆	☆	☆	T-13S38	62-313, 62-314....	Special	☆	☆	☆	Special	T-13S41
D10, D11.....	T-13R11	☆	☆	☆	☆	T-13S38	62-327, 62-337, 62-427, 62-437...	Special	T-13C26	☆	☆	T-78D46	T-81S01
C25, D30, D31, C40, SL45.....	T-13R12	☆	☆	☆	☆	T-13S38	NATIONAL CO., INC.						
M44.....	Special	T-13C26	☆	☆	T-78D46	T-81S01	DCSW-34, ACSW-58.....	☆	☆	☆	T-67C46 T-37C36	T-13A35 T-33A91 T-57A41	T-13S38 T-17S57 T-57S01
R71.....	T-13R02	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	NC-100.....	T-13R13	☆	☆	☆	T-13A35 T-33A91 T-57A41	T-13S38 T-17S57 T-57S01
B97, B98.....	Special	☆	☆	☆	Special	T-13S41	NOBLITT SPARKS INDUSTRIES						
LAUREHK RADIO MFG. CO.							508 AC DC, 608	☆	☆	☆	☆	☆	T-13S42
L-69.....	☆	☆	☆	☆	☆	T-13S38	518.....	T-13R11	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
L-600.....	☆	T-13C28	☆	☆	☆	T-13S42							
MAJESTIC RADIO & TELEVISION CO.													
50.....	☆	T-13C27	☆	☆	☆	T-13S38							
60.....	☆	T-13C28	☆	☆	☆	T-13S42							

☆ None Required.

THORDARSON TRANSFORMER REPLACEMENT ENCYCLOPEDIA

MODEL	Power Trans.	First Filter Choke	Second Filter Choke	First Audio Trans.	Second Audio Trans.	Output Trans.	MODEL	Power Trans.	First Filter Choke	Second Filter Choke	First Audio Trans.	Second Audio Trans.	Output Trans.
NOBLITT SPARKS INDUSTRIES—(Cont.)							PHILCO RADIO & TELEVISION CO.—(Cont.)						
618, 618A, 628, 628 CS, 638, 638 CS.....	T-13R12	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	98.....	T-13R14	☆	☆	☆	T-13A35 T-33A91 T-57A41	T-13S38 T-17S57 T-57S01
818, 828, 828A, 838CS, 848CS....	T-13R13	☆	☆	☆	☆	T-13S42	233G.....	☆	☆	☆	☆	☆	T-13S38
1237, 1247, 1247A	T-13R14	☆	☆	☆	☆	T-13S42	245.....	T-13R12	☆	☆	☆	☆	T-13S38
PACIFIC RADIO CORP.							642.....	☆	☆	☆	☆	T-13A35 T-33A91 T-57A41	T-13S38 T-17S57 T-57S01
30.....	☆	T-13C28	☆	☆	☆	T-13S42	PILGRIM ELECTRIC CORP.						
50, 60, 321-36, 321-37.....	T-13R12	☆	☆	☆	☆	T-13S38	NT.....	T-13R14	T-13C30	☆	☆	☆	T-13S38 T-17S57 T-57S01
80.....	Special	T-13C26	☆	☆	T-78D46	T-81S01	NTH.....	☆	T-13C28	☆	☆	☆	T-13S38 T-17S57 T-57S01
110, 150.....	Special	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	RJH, RJ.....	☆	☆	☆	☆	☆	T-13S42
PACKARD BELL COMPANY							PILOT RADIO CORP.						
5 "Kompak"....	T-13R12	☆	☆	☆	☆	T-13S38	23, P23, 25, P25, G162, G163, G185	☆	☆	☆	☆	☆	T-13S42
35H, 46B.....	T-13R11	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	G44, G45.....	☆	☆	☆	☆	T-13A35	T-13S43
50.....	Special	T-13C30	☆	☆	☆	T-13S41	X48, X49, G162A, G162B, G163A, G163B, 223, 623, 625....	☆	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
120.....	Special	☆	☆	☆	☆	T-13S38	G56, G57.....	Special	☆	☆	☆	☆	T-13S38
PATTERSON RADIO CO.							X-105, 193, 195, S295, S393, G576, G577.....	T-13R12	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
75A W, 75A W A, 85A W, 85A W A, 175A W, 175A W A, 185A W, 185A W A, 275A W, 275A W A, 285A W, 285A W A, 375A W, 375A W A, 385A W, 385A W A	T-13R13	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	X-304, X305....	☆	T-13C30	☆	☆	T-13A35 T-33A91 T-57A41	Special
87, 87A, 107, 107A, 127, 127A	T-13R13	☆	☆	☆	Special	T-13S38 T-17S57 T-57S01	G-528, G-529...	Special	☆	☆	☆	☆	T-13S41
105A W.....	T-13R14	☆	☆	☆	T-13A35 T-33A91 T-57A41	T-13S38 T-17S57 T-57S01	G-584, G-585...	T-13R14	☆	☆	☆	☆	T-13S41
PHILCO RADIO & TELEVISION CO.							G752, G753.....	T-13R11	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
37-9, 37-10, 37-11, 37-665, 37-2650.	Special	T-13C30	☆	☆	☆	T-13S38	M2203, M2205...	☆	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
37-62, 38-7, 38-8, 38-9, 38-10.....	T-13R12	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	X2253, X-2255...	Special	T-13C27	☆	☆	☆	T-13S38 T-17S57 T-57S01
37-93.....	T-13R11	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	RCA MFG. CO.						
37-624, 37-643, 38-39.....	Special	☆	☆	☆	T-78D46	T-81S01	5BT.....	☆	☆	☆	☆	T-78D46	T-81S01
37-641.....	☆	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	5XA, 5XA3, 5XA4	☆	☆	☆	☆	☆	T-13S38
37-690.....	Special	T-13C30 T-49C91	☆	☆	T-17D01	Special	5T1, 5TH, 5T5, 5T6, 5T7, 5T8, 6K2, 6K3, 6T5, 7T1, 7K1, 7U2, 85T1.....	T-13R12	☆	☆	☆	☆	T-13S38
37-2620.....	☆	☆	☆	☆	☆	T-13S38	7X, 86X.....	☆	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
37-2670.....	Special	T-13C30	☆	☆	T-13A35 T-33A91 T-57A41	T-13S38 T-17S57 T-57S01	8BT, 8BK, 8BT6, 8BK6....	Special	☆	☆	☆	T-78D46	T-81S01
38-1.....	Special	T-13C30	☆	☆	T-13A35 T-33A91 T-57A41	T-13S38 T-17S57 T-57S01	8T2, 8T11, 8K11, 8U, 8U2, 9K1.....	T-13R13	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
38-2, 38-3, 38-4, 38-5.....	Special	T-13C30	☆	☆	☆	T-13S38 T-17S57 T-57S01	9K3, 9U, 9U2, 10K1.....	T-13R14	☆	☆	☆	☆	T-13S42
38-12.....	Special	☆	☆	☆	☆	T-13S38	13K.....	Special	☆	☆	☆	T-13A35 T-33A91 T-57A41	T-13S41
38-14.....	☆	T-13C27	☆	☆	☆	T-13S38	15U.....	T-13R09	T-67C49	☆	☆	T-13A35 T-33A91 T-57A41	T-13S38 T-17S57 T-57S01
38-38.....	☆	☆	☆	☆	T-78D46	T-81S01	85B, 85BT, 86BK, 86BT....	☆	☆	☆	☆	T-78D46	T-81S01
38-60, 38-89....	Special	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	85T, R96, R97..	T-13R11	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
38-116.....	Special	T-67C49	☆	☆	Special	T-13S41	85T5, 86E, 86K, 86K7, 86T, 86T1, 87K, 87T, 88K, U101, U103.....	T-13R12	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
							811K, 812K.....	Special	☆	☆	☆	☆	T-13S38
							RADIO MFG. ENGINEERS INC.						
							RME69-AC.....	T-13R12	T-13C29	T-13C27	☆	☆	Special

☆ None Required.

THORDARSON TRANSFORMER REPLACEMENT ENCYCLOPEDIA

MODEL	Power Trans.	First Filter Choke	Second Filter Choke	First Audio Trans.	Second Audio Trans.	Output Trans.	MODEL	Power Trans.	First Filter Choke	Second Filter Choke	First Audio Trans.	Second Audio Trans.	Output Trans.
RADIO PRODUCTS CORP.							SONORA						
L6-M-1.....	T-13R12	T-13C28	☆	☆	☆	T-13S38 T-17S57 T-57S01	PR202.....	Special	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
L7.....	Special	T-13C27	☆	☆	T-78D46	T-81S01	PR300.....	☆	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
Z-2.....	T-13R11	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	SPARKS WITHINGTON CO.						
REMLER CO., LTD.							41A.....	☆	☆	☆	☆	T-13A34	☆
46, 52.....	T-13R12	☆	☆	☆	☆	T-13S38	75A, 475A, 478A	T-13R03	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
89.....	T-13R13	T-13C29	☆	☆	☆	T-13S41	427X, 437X, 457X.....	T-13R11	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
SEARS ROEBUCK & CO.							517, 537, 547X, 557, 567, 577, 617, 617X, 667, 667X	T-13R12	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
709, 719, Inter'l	T-13R14	☆	☆	☆	Special	T-13S38 T-17S57 T-57S01	727X, 727XD, 867, 877X.....	T-13R13	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
1942, 1972, 1994, 4486, 4488, 4488A, 4586, 4586A, 4587, 4588, 4588A.....	T-13R14	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	827X, 827XD, 987, 997X.....	T-13R16	☆	☆	☆	☆	T-13S42
1970, 1986, 1987, 4403, 4463, 4464, 4465, 4484, 4485, 4563, 4564, 4565, 4584, 4585, 100150, 101410..	T-13R12	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	1167.....	T-13R09	T-13C30	T-13C28	☆	T-13A35 T-33A91 T-57A41	T-13S38 T-17S57 T-57S01
4414, 4415, 4468, 4470, 4490, 4500, 4501, 4503, 4505, 4506, 4507.....	Special	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	STEWART-WARNER CORP.						
4418, 4421, 4430, 4434, 4521.....	Special	☆	☆	☆	☆	T-13S38	Chassis R-147, 1471 to 1479....	T-13R13	☆	☆	☆	☆	T-13S42
4419, 4426, 4426A, 4427, 4439, 4440, 4441, 4446, 4450, 4451, 4455, 4456, 4459, 4519, 4526A, 4539, 4546A, 4550, 4559.....	Special	T-13C26	☆	☆	T-78D46	T-81S01	R-148, 1481 to 1489....	T-13R15	☆	☆	☆	T-13A35 T-33A91 T-57A41	T-13S41
4569, 4589.....	T-13R13	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	R161D, 1611D to 1619D, R-162D, 1621D to 1629D	☆	☆	☆	☆	T-78D46	T-81S01
4604-5, 4624-5, 4634-5, 4724....	☆	☆	☆	☆	T-78D46	T-81S01	R-169, 1691 to 1695, R-172, 1721 to 1729....	T-13R11	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
7143.....	T-13R04	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	R-173, 1731 to 1739....	T-13R12	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
7172X.....	☆	Special	☆	☆	☆	T-13S38 T-17S57 T-57S01	STROMBERG-CARLSON TEL. MFG. CO.						
SENTINAL RADIO CORP.							126H, 126L, 127H, 127M....	☆	☆	☆	☆	Special	T-13S38 T-17S57 T-57S01
6A, 19A.....	T-13R13	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	150L, 150LB....	T-13R15	T-67C49	☆	☆	Special	T-13S41
30A, 48A, 52A, 54A, 70A.....	T-13R11	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	160L, 160LB, 180L, 180LB....	T-13R16	T-67C49	☆	☆	T-17D01	T-13S41
33B, 38B, 39B..	☆	☆	☆	☆	T-78D46	☆	140H, 140HB, 140K, 140KB, 140L.....	T-13R14	T-13C30	☆	☆	Special	T-13S38 T-17S57 T-57S01
36L, 6900.....	☆	☆	☆	☆	T-13A35 T-33A91 T-57A41	T-13S38 T-17S57 T-57S01	225 ACDC....	☆	T-13C28	☆	☆	☆	T-13S38 T-17S57 T-57S01
40B, 7200.....	T-13R12	☆	☆	☆	☆	T-13S38	228L, 228LB, 228H, 228HB, 229P, 230H, 230HB, 230L, 230LB, 231F, 231FB, 231R, 231RB, 231P, 231PB.....	T-13R12	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
49B, 65B.....	Special	T-13C27	☆	☆	T-78D46	T-81S01	250L, 250LB....	T-13R16	T-67C49	☆	☆	☆	T-13S41
53A.....	T-13R14	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	L. TATRO PRODUCTS CO.						
55U, 71U.....	☆	T-13C27	☆	☆	☆	T-13S38 T-17S57 T-57S01	U5226, V5226, T6216.....	Special	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
60B.....	☆	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	TRANSFORMER CORPORATION OF AMERICA						
SHELLEY RADIO CO.							TC-6, TC-39....	T-13R12	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
35C, 35C-AW, 37C, 48A.....	T-13R12	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	TC-28, TC-29...	☆	T-13C28	☆	☆	☆	T-13S38 T-17S57 T-57S01
SIMPLEX RADIO CO.							TC-42, TC-43, TC-44.....	T-13R06	☆	☆	☆	T-13A35 T-33A91 T-57A41	T-13S38 T-17S57 T-57S01
N, P, R, (AC)...	T-13R03	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	TC-65.....	☆	T-13C29	☆	☆	T-13A35 T-33A91 T-57A41	Special
P (DC), R (DC)	☆	T-13C29	☆	☆	☆	T-13S38 T-17S57 T-57S01							

☆ None Required.

THORDARSON TRANSFORMER REPLACEMENT ENCYCLOPEDIA

MODEL	Power Trans.	First Filter Choke	Second Filter Choke	First Audio Trans.	Second Audio Trans.	Output Trans.	MODEL	Power Trans.	First Filter Choke	Second Filter Choke	First Audio Trans.	Second Audio Trans.	Output Trans.
TRAVLER RADIO AND TELEVISION CORP.							WESTONE RADIO CORP.						
5 tube Batt.....	Special	☆	☆	☆	T-78D46	T-81S01	70, 70C, 11, 12..	T-13R03	☆	☆	☆	☆	T-13S38
521, 522.....	☆	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	WILCOX-GAY CORP.						
635M.....	T-13R12	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	6A5, 6B8, 6F6, 6FB6.....	T-13R12	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
TROY RADIO AND TELEVISION COMPANY							6D6.....	☆	T-13C27	☆	☆	☆	T-13S38 T-17S57 T-57S01
55.....	T-13R11	☆	☆	☆	☆	T-13S38	ZENITH RADIO CORP.						
57, 67, 67SW, 79, 95, 100.....	T-13R12	☆	☆	☆	☆	T-13S38	4B231.....	Special	☆	☆	☆	☆	T-13S38
179.....	☆	☆	☆	☆	☆	T-13S42	4F133, 4F227, 5407, 5408.....	Special	☆	☆	☆	☆	T-13S43
ULTRAMAR MFG. CORP.							5F134, 5F166, 5518.....	Special	T-13C27	☆	☆	T-78D46	T-81S01
801, 802.....	T-13R12	☆	☆	☆	☆	T-13S38	5F233, 5F251, 5522.....	☆	☆	☆	☆	T-78D46	T-81S01
UNITED AMERICAN BOSCH CORP.							5J217, 5J247, 5J255, 5524.....	Special	☆	☆	☆	☆	T-13S38
306.....	T-13R14	Special	☆	☆	T-74A31	T-13S38 T-17S57 T-57S01	5R123, 5R135, 5R165, 5R216, 5R226, 5R236, 5S201, 5S218, 5S220, 5S228, 5S237, 5S250, 5S252, 5519, 5521, 5526.....	T-13R12	☆	☆	☆	☆	T-13S38
515.....	T-13R12	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	6D202, 6D219, 6D221, 6D238, 5639.....	☆	T-13C27	☆	☆	☆	T-13S42
604B.....	☆	T-13C28	☆	☆	☆	T-13S42	6J230, 6J257, 5642, 7J232, 7J259, 5711.....	Special	☆	☆	☆	T-78D46	T-81S01
THE WALGREN CO.							6S203, 6S222, 6S223, 6S229, 6S239, 6S241, 6S254, 6S256, 7S204, 7S232, 7S240, 7S242, 7S258, 7S260, 7S261, 8S129, 8S154, 5644, 5801, 5638.....	T-13R12	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
B25-RS.....	☆	☆	☆	☆	T-78D46	T-81S01	7D203, 7D222, 7D223, 7D229, 7D239, 7D241, 7D243, 7D253, 5710.....	☆	☆	☆	☆	☆	T-13S42
55RS.....	T-13R12	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	9S203, 9S232, 9S242, 9S244, 9S262, 9S263, 9S264, 5905.....	T-13R13	☆	☆	☆	☆	T-13S38
57RS, 370.....	☆	T-13C27	☆	☆	☆	T-13S38 T-17S57 T-57S01	10S130, 10S147, 10S153, 10S155, 10S156, 10S157, 10S160, 1004, 12U158, 12U159, 1203.....	T-13R15	T-13C30	☆	☆	T-13A35 T-33A91 T-57A41	T-13S41
WARWICK MFG. CO.							12S205, 12S232, 12S245, 12S265, 12S266, 12S267, 12S268.....	T-13R15	☆	☆	☆	☆	T-13S41
501.....	☆	Special	☆	☆	☆	T-13S38 T-17S57 T-57S01	15U246, 15U269, 15U270, 15U271, 15U272, 15U273, 1501.....	Special	T-67C49	☆	☆	☆	Special
518, 613, 633....	T-13R11	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	258, 268, 278, 280, 281, 288, 289, 478, 558, 568, 578, 589, 590.....	T-13R04	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01
551, 601.....	T-13R12	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	520, 521, 602, 605, 608, 611, 615, 2035.....	T-13R06	T-13C30	☆	☆	T-67D78	T-67S52
651.....	Special	☆	☆	☆	T-78D46	T-81S01	2038.....	T-56R05	T-13C30	☆	☆	☆	T-67S52
WELLS GARDNER & COMPANY							ZEPHYR RADIO CO.						
OEL.....	T-13R14	☆	☆	☆	Special	T-13S38 T-17S57 T-57S01	20A6, 21A6, 22A6	☆	☆	☆	☆	T-78D46	T-81S01
OF, 7E.....	☆	☆	☆	☆	T-78D46	T-81S01	20X7, 21X7, 22X7.....	☆	T-13C27	☆	☆	☆	T-13S38
5F, 5FL, 5K, 5KL, 7F, 7FL, 7J.....	T-13R12	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01	25Y11.....	T-13R14	T-13C30	☆	☆	☆	T-13S41
5H.....	Special	☆	☆	☆	☆	T-13S43							
WESTERN AUTO SUPPLY													
S-721.....	Special	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01							
S-724.....	☆	☆	☆	☆	T-78D46	T-81S01							
S-727.....	T-13R06	T-13C29	☆	☆	T-13A35 T-33A91 T-57A41	T-13S38 T-17S57 T-57S01							
WESTINGHOUSE ELECTRIC SUPPLY CO.													
WR-102A.....	☆	T-13C27	☆	☆	☆	T-13S42							
WR-103, WR-103-A, WR-116, WR-116-X, WR-316, WR-316-X	☆	T-13C27	☆	☆	☆	T-13S38 T-17S57 T-57S01							
WR-211, WR-212, WR-311, WR-312	T-13R12	☆	☆	☆	☆	T-13S38 T-17S57 T-57S01							
WR-315.....	T-13R15	☆	☆	☆	Special	T-13S41							